

# Operating device TouchCenter plus

## Intrusion

The newly developed graphics operating device TouchCenter plus as successor of TouchCenter Tuxedo offers with its new user interface simple, fast, intuitive and secure ease of use.

Intruder alarm systems of the series MB-Secure, 561-MB100/MB48/MB24/MB256 plus and MB12 can comfortably be controlled by using the color touchscreen. The connection to the control panel is realized via BUS-2.

Important for the operation and display of system information of a hazard detection system is above all reliability, rapid acquisition of information and easy operation. These are vital prerequisites for daily use that the TouchCenter plus fulfils in every respect.

The TouchCenter plus for BUS-2 enables your hazard detection system to be intuitively dialog managed. By touching a displayed button on the touchscreen, the desired operating function can be selected directly and executed. Clear and unambiguous buttons and additional symbols provide maximum operating comfort. The 3 LEDs on the front show the current operating states of the system even if the graphics display is not activated. Further status and operating information is accurately and clearly displayed.

An IK2/proX1 and IK3/proX2 reader for user authorization is integrated into the Keypad. The reader can only be used in conjunction with a MB-Secure panel (from V03.05).

An integrated on-board Ethernet connection allows you to view live video for one IP camera directly on the graphic keypad. If the camera is movable and tiltable, this can be controlled directly on the TouchCenter plus.



The TouchCenter plus gets an optical appreciation by use as an electronic picture frame with slideshow functionality.

The project-based programming of the intruder alarm system and the TouchCenter plus will be done via a PC/laptop with the appropriate software package.


## FEATURES

- New graphical user interface
- Different languages available
- Clear display of the system status
- Connection to control panel via BUS-2
- (except BUS-2 loop module Item no. 013220.07.10)
- Up to 16 TouchCenter plus can be connected to a panel
- Integrated reader for proX1/IK2 / proX2/ IK3 data carriers
- (used in conjunction with a MB-Secure panel)
- IP camera can be connected and controlled directly
- 7" color display with touch screen function
- Individual graphic or own photo to be set as wallpaper
- Highlighted with use as an electronic photo frame with slideshow functionality
- Flash technology for updates
- Modular design
- Multiple control units can be arbitrarily combined horizontally and vertically to each other
- s.m., f.m. and cavity wall installation possible
- Cover contact, tear off contact with surface mounting
- VdS-approval Class C
- As per EN 50131-3, Grade 3
- SES certification
- Alternative use as time & attendance terminal with NovaTime-Software
- Create and play voice-mails

## BENEFITS

- Clear display of the system status
- Simple dialog guided intuitive user guidance with symbols
- Cost reduction through integrated video functionality
- Investment for the future
- (Functionality grows with new functions of the MB-Secure)

## Possible combinations



The TouchCenters can be arrayed vertically and/or horizontally and fixed (see example opposite). TouchCenters, both surface-mounted and flushmounted, can be individually arranged and operated. The required mounting accessories are included in the respective scope of delivery.

## Example slideshow



## Example user guidance




## Modular design


The delivery status of the TouchCenter plus consists of 3 components: bezel, front unit with electronics and backplane.

### Standard


Bezel



Front complete with electronics



Case back deep for s.m. mount




#### Note:


With a combination of TouchCenter and LED- and LED/LCD keypads, the case back deep must be used also for LED- and LED/LCD keypads (Standard equipment is case back low).

### Option


Flushmount installation box



Metal box f. masonry mount



### Mounting example



## Softwarevoraussetzungen

MB12/561-MB100\*/HB24/HB48\*/MB24/MB48  
\* Art.-Nr. mit Index .10

- 1-RAM Version

V08.16

- 2-RAM Version,  
falls Leistungsmerkmale der V09 gewünscht werden

V08.16 oder...  
V09.12

WINFEM Advanced

V07.13

561-MB256 plus

V03.18

WINFEM Advanced

V07.13

MB-Secure

V04.xx

IQ PanelControl


V04.xx

TouchCenter plus


V02.xx

## Abmessungen


### Case back deep



### Flushmount installation box



### Metal box for masonry mount



# Operating device TouchCenter plus Security

TECHNICAL DATA	
Nominal operating voltage U <sub>b</sub>	12 V DC (voltage supply via BUS-2)
Operating voltage range	10 V to 15 V DC
Current consumption at 12 V DC	140 mA (no load) 225 mA (max. display brightness) 260 mA (max. display brightness + buzzer)
Integrierter Leser (unterstützt ab V01.06)	for IK2/proX1 and IK3/proX2 keycard
Frequenzbereich	Sendeleistung: Kartenleser 119 kHz bis 135 kHz, 20 dBµA/m / WiFi 2,412 GHz bis 2,475 GHz, 10 mW
Class of protection as per EN 60529	IP30
Environmental Class as per VdS	II
Environmental class as per EN 50131-3	Class II
Operating temperature range	-5 °C to +45 °C
Storage temperature range	-25 °C to +60 °C
Relative humidity	93% non-condensing
Weight	610 g
Screen size (diagonal)/resolution	7" (17,78 cm)/800 x 480 pixels
Screen format	16 : 9
Dimensions (W x H x D)	218 x 162 x 35 mm
Housing colour	white (similar to RAL 9016), optional grey and black
VdS-Approval	requested
EN compliance	requested
SES certificate	requested




013003 (white)



013004 (grey)



013005 (black)



013050

## ORDERING INFORMATION

Item no.	Description	Accessories
013003	Keypad TouchCenter plus, white Set, consists of: - TouchCenter plus front device complete with electronics, white - Bezel, white - Case back deep, white	013030 Touch bezel, white 013032 Touch bezel, gray 013034 Touch bezel, black 013036 Touch bezel, clear, printable 013040 Case back deep, white 013041 Case back deep, gray 013042 Case back deep, black 013046 Flushmount installation box, white 013047 Flushmount installation box, gray 013048 Flushmount installation box, black 013050 Metal box for masonry mount of LED/LCD/touch keypad 013051 FM-Frame for TC plus 013052 Console House Top for TC plus 013053 Console House Base for TC plus
013004	Keypad TouchCenter plus, gray Set, consists of: - TouchCenter plus front device complete with electronics, gray - Bezel, gray - Case back deep, gray	
013005	Keypad TouchCenter plus, black Set, consists of: - TouchCenter plus front device complete with electronics, black - Bezel, black - Case back deep, black	

### For more information:

[www.security.honeywell.de](http://www.security.honeywell.de)

### Honeywell Commercial Security Novar GmbH

Johannes-Mauthe-Straße 14  
72458 Albstadt  
Germany  
+49 7431 801-0  
[www.honeywell.com](http://www.honeywell.com)

HSFI-TCPMB-02-EN(1218)DS-H  
December 2018  
© 2018 Honeywell International Inc.