


Extension housing for SZI 192 detector zones IQ8Control




Part-No. 789302

The housing can be used to mount additional modules, e.g. an esserbus transponder.

Output voltage	12 V DC
Current consumption	1.5 mA when LED activated
Quiescent current	approx. 5 mA
Battery capacity	2 x 12 Ah, 2 x 24 Ah in extension housing
Ambient temperature	-5 °C ... 45 °C
Type of protection	IP 30
Housing	ABS, 10% glass fiber reinforced, V - 0
Air humidity	< 95 %
Color	gray similar to Pantone 538
Weight	approx. 5 kg
Dimensions	W: 450 mm H: 320 mm D: 185 mm

 This housing cannot be used if an operating module front with single zone indicator unit for 64 zones is already fitted. A SZI unit can only be used in combination with an operating module front.

 Housing complete with standard rear panel, single zone indicator front for 192 detector zones and material for attaching to the existing panel housing.