

# ICP-MAP0115 Power enclosure kit

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Can be added to a MAP Panel Enclosure Kit to increase the back-up time
- ▶ Suitable for a power supply and two sets of 2x 12 V / 38-45 Ah batteries

The MAP Power Enclosure Kit (ICP-MAP0115) contains one MAP Power Enclosure, one MAP Panel Enclosure Tamper Switch, one MAP Enclosure Lockset, one MAP AC Terminal Block, and an accessory pack containing connection cables. The MAP Power Enclosure is designed to hold up to two sets of 2x 12 V / 38-45 Ah batteries.

## Certifications and approvals

Region	Certification	
Europe	CE	[MAP 5000 Modules]
Poland	TE-CHOM	03-16-o [ICP-MAP5000]

## Parts included

Quantity	Component
1	MAP Power Enclosure
1	Accessory pack <ul style="list-style-type: none"> <li>• 2 MAP Bosch Data Bus (BDB) cables, extra long (ICP-MAP0135)</li> <li>• 1 MAP battery cable, long</li> <li>• 1 MAP battery jumper ring cable (ICP-MAP0142)</li> </ul>

Quantity	Component
	<ul style="list-style-type: none"> <li>• 1 MAP panel enclosure tamper switch (ICP-MAP0050)</li> <li>• 1 MAP AC terminal block (ICP-MAP0065)</li> <li>• 1 MAP enclosure lockset (ICP-MAP0060)</li> </ul>
1	Hardware pack <ul style="list-style-type: none"> <li>• 7 TORX screws (M4 x 8mm, type A)</li> </ul>
1	Installation template

## Technical specifications

### Mechanical

Dimension in cm (H x W x D)	65.8 x 44.3 x 19.35
Weight in g	1566
Material	1.5 mm cold rolled steel
Color	White

### Environmental

Protection class	IP30
Security level	IK06

Environmental class	II: EN50130-5, VdS 2110
Usage	Indoor

### Ordering information

#### Power enclosure kit

Kit contains one MAP Power Enclosure, one MAP Panel Enclosure Tamper Switch, one MAP Enclosure Lockset, one MAP AC Terminal Block, and an accessory pack containing connection cables.

Order number **ICP-MAP0115**

#### Accessories

##### AC terminal block

Terminal block to connect supply voltage to the MAP power supply 150W.

Order number **ICP-MAP0065**

##### Enclosure lockset

Lock, two keys, and two warranty seals for use on MAP Panel Enclosure, MAP Power Enclosure, or MAP Expansion Enclosure.

Order number **ICP-MAP0060**

##### Panel enclosure tamper switch

Fits in the MAP Panel and MAP Power Enclosures.

Order number **ICP-MAP0050**

#### Represented by:

**Europe, Middle East, Africa:**  
Bosch Security Systems B.V.  
P.O. Box 80002  
5600 JB Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
emea.securitysystems@bosch.com  
emea.boschsecurity.com

**Germany:**  
Bosch Sicherheitssysteme GmbH  
Robert-Bosch-Ring 5  
85630 Grasbrunn  
Germany  
www.boschsecurity.com

**North America:**  
Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
onlinehelp@us.bosch.com  
www.boschsecurity.us

**Asia-Pacific:**  
Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia